

Unipolar Hall Effect Switch IC

Features:

- Operates from 2.4V to 26V supply voltage with reverse voltage protection
- Operates with magnetic fields from DC to 15kHz
- On-chip Hall Sensor
- On-chip temperature compensation circuitry minimizes shifts in on and off points and hysteresis over temperature and supply voltage
- Ideal sensor for speed measurement, revolution counting, positioning, and DC brushless motors
- On (L) with magnetic South pole and Off(H) without magnetic field or with magnetic North pole

Functional Description:

WSH134 is designed to integrate Hall sensor with output driver together on the same chip, it is suitable for speed measurement, revolution counting, positioning. It includes a temperature compensated voltage regulator, a differential amplifier, a Hysteresis controller and a open-collector output driver capable of sinking up to 20mA current load. An on-chip protection resistor is implemented to prevent reverse power fault.

The temperature-dependent bias increases the supply voltage of the hall plates and adjusts the switching points to the decreasing induction of magnets at higher temperatures. Subsequently, the output can keep switching on/off on more precise switch point regardless to the ambient temperature. WSH134 are rated for operation over temperature range from –40° C to 125 °C and voltage ranges from 2.4V to 26V.

Pin Descriptions:

Name	P/I/O	Pin#	Description			
Vdd	P	1	Positive Power Supply			
Gnd	О	2	Ground			
Vout	О	3	Output Pin			

Absolute Maximum Rating (at Ta=25°C)

Supply Voltage Vcc ----- 26V






Output breakdown Voltage		t _(breakdown)	30V	
Magnetic flux density	В		Unlimited	
Reverse Protection Voltage	Vr		26V	
Output ON Current (continuous)	Ic		25mA	
Operating Temperature Range	Ta		(-40°C to +125°C)	
Storage Temperature Range	Ts		(-65°C to +150°C)	
Package Power Dissipation	Pd		500mw	

Electrical Characteristics:

$(T=+25^{\circ}C,$	Vcc=2.4V	to 26V)
	V CC—2.T V	10 40 1

Characteristic	Symbol	Test Conditions	Min	Тур	Max	Units
Supply Voltage	Vcc		2.4		26	V
Output Saturation Voltage	Vout (sat)	Vcc=12V,Ic=10mA B > Bop		0.2	0.6	V
Output Leakage Current	Ileakage	Vcc=12V, B <brp< td=""><td>_</td><td><0.1</td><td>10</td><td>uA</td></brp<>	_	<0.1	10	uA
Supply Current	Isupply	Vcc=12V,Output Open	_	2.0	5	mA
Output Rise Time	Tr	Vcc=12V,RL=2K Ω CL=20Pf	_	1.0	10	μ s
Output Falling Time	Tf	Vcc=12V,RL=2K Ω CL=20Pf	_	0.3	1.5	μs

Function Block:






Magnetic Characteristics:


Characteristic	Symbol	Grade	Min.	Тур.	Max.	Unit
Operating Point	Bop		+50	+150	+250	Gauss
Release Point	Brp		+30		+210	Gauss
Hysteresis Window	Bhys		10	30	60	Gauss

^{*+} mean South magnetic field, 1mT=10 Gauss

Order Information:



Application Circuit:




South



Package Information:

TO-92S:



SOT23:

